





INSTRUCTIONS

CONNECTING THE BATTERIES TO THE INVERTER

Preliminary steps to take when connecting your inverter/charger at the beginning of the season.

By following these simple steps, you can significantly extend the lifespan of the batteries and the inverter.

- 1 Turn on the battery. If the battery has one or more switches, be sure to turn them all on. Power button depressed = ON. 
- 2 Connect the battery's negative terminal to the electrical system busbar.

- 4  Install the resistor between the battery's positive terminal and the inverter's positive cable: hold the resistor for 10 seconds (the current will slowly flow through the resistor). The current will flow from the battery to the inverter.   **3** Make sure the power to the inverter is turned off.

- 5 After 10 seconds, you can remove the resistor and connect the inverter's positive cable to the battery.
- 6 Everything is ready! You can now turn on your inverter.

volthium.com | 1-888-989-9586

 YouTube

